

QS5 Cam Starter

APPLICATION

QS5 can starter is mainly used to start forward or backward and stop directly three-phase asynchronous electric motor with AC 50Hz, voltage up to 500V and capacity up to 7.5-30KW. It can also be used for changeover from one kind of circuit to another.

SPECIFICATION

Type	Mark	Rated current (A)	Motor control capacity (HP)	Electrical life (time)	Mechanical life (time)	Frequency of operation (perhr)	Applications	Position of lever
QS5-15A	I-O	15	5.5	10000	250000	200	ON-OFF switching	0-60
QS5-30A		30	10					
QS5-15N	I-O- I	15	5.5	8000	20000	180	Forward & reverse	60-0-60
QS5-30N		30	10					
QS5-15P/3	I-O- II	15	5.5				for 3 pole two circuits	60-0-60
QS5-30P/3		30	10					
QS5-63A	I-O	63	22				ON-OFF switching	0-60
QS5-100A		100	30					
QS5-63N	I-O- I	63	22	8000	20000	180	Forward & reverse	60-0-60
QS5-100N		100	30					
QS5-63P/4	I-O- II	63	22				for 3 pole two circuits	60-0-60
QS5-100P/4		100	30					



QS5-15P



QS5-30A



QS5-30N



QS5-63A



QS5-100A



GZ-100A